

USER'S MANUAL

MODEL: 5403

76MM ELECTROMAGNET

Date Sold: _____

Serial number: _____

PROPRIETARY

THIS DOCUMENT CONTAINS CONFIDENTIAL INFORMATION
PROPRIETARY TO GMW ASSOCIATES. IT MUST NOT BE REPRODUCED
OR DISCLOSED TO OTHERS OR USED IN ANY WAY EXCECPT FOR THE
INSTALLATION, OPERATION OR MAINTENANCE OF GMW ASSOCIATES
PRODUCTS.

TABLE OF CONTENTS

SPECIFICATIONS	Section 1
Table 1 Model 5403 General Specifications	
Table 2 Model 5403 Electrical and Water Connections	
 WARNINGS [Refer to this section before operation of Electromagnet]	Section 2
 INSTALLATION	Section 3
Unpacking Instructions	
Mounting Position	
Pole Selection and Installation	
Electrical Circuit	
Interlocks	
Cooling	
 OPERATION	Section 4
General	
Calibration	
Field Control Operation	
 MAINTENANCE	Section 5
 STANDARD OPTIONS	Section 6
Motorized Rotating Drive	
Probe Holder	
 CUSTOM OPTIONS	Section 7
 EXCITATION CURVES	Section 8
 TEST DATA	Section 9
 DRAWINGS	Section 10
Elmwood 3450 Thermostats	
Drawing 11610500 5403 Electromagnet General Assembly	
Drawing 11900740 5403/P62B-3066 Electromagnet Electrical Assembly	
Drawing 13900240 5403/P62B-3066 Electromagnet Electrical Wiring	

Continued...

DRAWINGS

Drawing 11900240 5403/BOP 20-40 Electromagnet Electrical Assembly
Drawing 13900110 5403/BOP 20-40 Electromagnet Electrical Wiring
Drawing 13900090 5403 BOP 2020/2020 Electrical Wiring
Drawing 11900270 5403 Electromagnet to Rolling/Rotating Base Assembly
Drawing 11900280 5403 Electromagnet to Rolling Base Assembly
Drawing 11900290 5403 Electromagnet to Rotating Base Assembly
Drawing 11900260 5403 Electromagnet Assembly to Vertical Mount
Drawing 11803430 Electromagnet Rolling/Rotating Base Assembly
Drawing 11803170 Electromagnet Rolling Base Assembly
Drawing 11802090 Electromagnet Rotating Base Assembly
Drawing 17612640 5403 Electromagnet Vertical Mount Bracket
Drawing 17612650 5403 Electromagnet Angle Bracket
Drawing 18900030 5403 Electromagnet Tool Kit
Drawing 17612620 5403 Pole, Cylindrical (76mm)
Drawing 17612630 5403 Pole, Tapered (38mm)
Drawing 18800281 5403 Shipping Crate Assembly
Drawing 17803500 5403 Pole Packing Box

Section 1
SPECIFICATIONS
Table 1. Model 5403 Specifications

Pole Diameter:	76mm (3 inch)
Pole Gap:	0 - 76mm (0 to 3 inch)
Standard Pole Face:	75mm (3 inch) cylindrical 38mm (1.5 inch) tapered
Coils (series connection)	
coil resistance (20°C)	0.45 Ohm
max resistance (hot)*	0.55 Ohm
max power (air)	20A/10V (0.2kW)
max power (water)	50A/25V (1.25kW)
Self Inductance	60mH
Water Cooling (18°C)	2 liters/m (0.5 US gpm) 0.5 bar (8 psid)
Overtemperature Interlock	Elmwood 3450G thermostat part number 3450G 611-1 L50C 89/16 mounted on each coil and wired in series. Contact rating 120Vac,0.5A. Closed below 50°C.
Dimensions	Drawing 11610500 604mm W x 270mm D x 359mm H 23.8 inch W x 10.6 inch D x 14.1 inch H
Weight	124 kg (275 lb)

***CAUTION - The value of maximum coil resistance given should not be exceeded. At this resistance the coils are at maximum safe temperature for continuous operation.**

Section 1
SPECIFICATIONS

Table 2. Model 5403 Electrical and Water Connections

DC Current (as seen from the front refer to Drawing 11610500)

Right hand terminal:	Negative
Left hand terminal:	Positive

Ground

An M4 screw (Item 24 on drawing 11610500) is inside the terminal cover to enable the magnet frame to be grounded according to local safety regulations. It is normally appropriate to connect the magnet frame to the power supply ground.

Interlocks (refer to Drawing 11610500).

The temperature interlock wiring connections are made directly onto the temperature thermostats (Item 17 on drawing 11610500).

Water (refer to Drawing 11610500).

Outlet	1/8 inch NPT
Inlet	1/8 inch NPT

(mating couplings for 1/4 inch hose provided)

CAUTION - Ensure that the high current connections are tight. Loose connections may lead to oxidation and overheating. The field stability may be degraded and the current terminations damaged.

Section 2

WARNINGS

REFER TO WARNINGS BELOW BEFORE OPERATING ELECTROMAGNET

1 Personnel Safety

In operation the magnet fringing field is in excess of 0.5mT (5G). This can cause malfunctioning of heart pacemakers and other medical implants. We recommend that the fringing field should be mapped and warning signs be placed outside the 0.5mT (5G) contour. Entry to this region should be restricted to qualified personnel.

2 Draw/Clamp Bolts

Before operation always ensure that the draw bolts (item 5 on drawing 11610500) are properly engaged and have their heads firmly against the cap *and* that all clamp bolts (item 18 on drawing 11610500) are firmly tightened. Ensure that the poles are arranged so that that pole gap is approximately centered between the coils.

3 Ferromagnetic Objects

During operation the magnet exerts strong magnetic attraction towards ferromagnetic objects in the near vicinity of its pole gap or coils. Loose objects can be accelerated to sufficient velocity to cause severe personnel injury or damage to the coils or precision pole faces if struck. Keep ferromagnetic tools clear!

4 Arcing

This magnet stores considerable energy in its field during operation. Do not disconnect any current lead while under load or the magnetic field energy will be discharged across the interruption causing hazardous arcing.

5 Coil Hot Resistance

Do not exceed the maximum coil hot resistance given in the specifications or coil overheating and possible damage may occur.

6 Interlocks

These should *always* be connected if the magnet is operated unattended, to avoid the possibility of coil overheating caused by excessive power dissipation or inadequate cooling.

7 Watches, Credit Cards, and Magnetic Disks

Do not move magnetically sensitive items into the close vicinity of the magnet. Even some anti-magnetic watches can be damaged when placed in close proximity to the pole gaps during operation. Credit cards, and magnetic disks are affected by magnetic fields as low as 0.5mT (5G). Depending on the previous operating field and the pole gap, the remanent field in the gap can be in excess of 50G (5mT) with the magnet power supply off or disconnected.

Section 3

INSTALLATION

Caution: This is a heavy system. All movement, lifting and installation of the 5403 Electromagnet must be under the supervision of an experienced person to prevent the possibility of serious injury or damage to the Electromagnet and associated equipment.

Unpacking Instructions and Damage Inspection

To unpack the electromagnet please use the following procedure (Refer to Drawing 18800281).

1. First remove all of the "Hex Head Screws" located at the lower edge of all the side panels of the "Crate Top Cover".
2. Gently rock the "Crate Top Cover" to work it loose from the shipping crate base.
3. Grip the side panels of the Crate Top Cover. Lift "Crate Top Cover" high enough to clear top of electromagnet, walk cover sideways to a clear area and place on floor.
4. Inspect the magnet to ensure that no damage has occurred to the magnet in shipment. If damage is evident report the damage in detail to the shipper for claim and simultaneously notify GMW in case assessment of the damage must be made. If no damage is found proceed with magnet unpacking and installation.
5. Remove the M12 hex head coach bolts that secure the magnet to the shipping crate base".
6. Install M12 lifting eyebolt and washer to top of magnet yoke, screw down firmly.
7. The magnet is now prepared for final installation. Follow the appropriate procedure for direct or base mounting listed below.

Direct Mounting

1. With suitable lifting equipment e.g. 250kg (550 lb) minimum safe lifting rating, lift magnet 50mm (2") clear of shipping crate base.
2. Slide shipping crate base clear.
3. Lower magnet to 50mm (2") above floor.
4. Move magnet to final location and bolt magnet down through the four mounting holes provided in the magnet angle bracket (Item 7 on drawing 1610500).

Rolling or Rolling/Rotating Base Mounting (refer to Drawing 11900270)

Caution do not attempt to move magnet and rolling base or rolling/rotating base until the magnet has been firmly bolted down to the base.

1. To mount on rolling base or rolling/rotating base lift magnet from BOTH EYEBOLTS high enough to clear top of base.
2. Slide rolling base or rolling/rotating base underneath, lower magnet to 12mm (0.5") above base top surface.
3. Position rolling base or rolling/rotating base so the tapped holes in the base are aligned with the angle mounting bracket holes. Lower the rolling base support legs until they contact the floor, to prevent the base from accidentally moving horizontally.
4. Lower magnet onto rolling base or rolling/rotating base assembly.
5. Secure magnet to rolling base or rolling/rotating base with M10 x 25 long Hex Head Bolts.
6. Raise the support legs and move magnet and rolling base or rolling/rotating base to desired location.

Section 3

INSTALLATION

Rolling or Rolling/Rotating Base Mounting (Continued)

7. Screw down the four support legs located on each corner of the rolling or rolling/rotating base until the wheels clear the floor by 6mm (.25").
8. Secure the support legs with the locknut.
9. Secure rolling/rotating base to an adequate concrete floor to prevent movement and possible injury to personnel during an earthquake.

Pole Selection and Installation (Refer to drawing 11610500).

Using the field uniformity and induction curves determine the most desirable pole; cylindrical or tapered. In general:

If a uniform field is required use a cylindrical pole.

If a high field is required use a tapered pole.

Pole removal (refer to drawing 11610500).

1. Turn off the power supply.
2. Loosen the four pole clamping bolts (item 18 on drawing 11610500).
3. Adjust the 5403 magnet for maximum pole gap, i.e. 75mm (3 inch). To adjust the pole gap insert the 17mm hex key wrench (item 2 on drawing 1890030) into the drive bolt (item 5 on drawing 11610500). Rotate clockwise until the pole is fully retracted. Repeat this operation for the other pole.
4. Remove the six cap securing screws (item 28 on drawing 11610500).
5. Pull the pole and cap assembly about 75mm (3 inches) out of the magnet yoke.
6. Grip the cap with one hand and support the pole with the other hand. Remove the pole and cap assembly taking care that the pole face is not damaged by contacting the magnet yoke.
7. Remove the cap (item 4 on drawing 11610500).

Pole fitting (refer to drawing 11610500).

1. Ensure the poles and pole sleeves are clean and free from debris.
2. Reverse the above pole removal sequence above.

Electrical Circuit

Never connect or remove cables from the magnet with the power supply connected. The stored energy in the magnet can cause arcing resulting in severe injury to personnel or equipment damage.

The magnet has two coils which are connected in series, (Refer to drawing 11610500). The power supply cables should be connected directly to the dc current terminals marked + and -. Recommended current cable for the 5403 is stranded copper of 16mm² cross section (4 AWG).

Because the magnet stores a significant amount of energy in its magnetic field, special care should be taken to insure that the current terminations are secure and cannot work loose in operation. Local heating at the terminations can cause rapid oxidation leading to a high contact resistance and high power dissipation at the terminals. If left unattended this can cause enough local heating to damage the terminals and the coils.

Section 3

INSTALLATION

The 5403 Interlocks

The Model 5403 has two thermostats, Elmwood 3450G Part Number 3450G611-1 L50C 89/16. They are located on the center coil cooling plate and wired in series. The thermostats are normally closed, opening when the coil central cooling plate temperature exceeds $50^{\circ}\text{C} \pm 3^{\circ}\text{C}$.

Cooling

The Model 5403 can be operated to an average coil temperature of 70°C . Assuming an ambient laboratory temperature of 20°C and a temperature coefficient of resistivity for copper of $0.0039/^{\circ}\text{C}$, the hot resistance of the coil should not exceed 20% more than the ambient temperature "cold" resistance. The coil thermostat will open when either center coil cooling plate temperature exceeds approximately 50°C . Clean, cool ($16^{\circ}\text{C} - 20^{\circ}\text{C}$) water at 2 l/min at 0.5 bar (8 psid) should be used to cool the 5403 magnet.

The cooling copper tubes are electrically isolated from the coils to avoid electrochemical corrosion. A 50 micron filter should be placed before the input to the magnet to trap particulate and avoid unreliable operation of the water flow switch interlock if fitted.

For continuous operation of the magnet it may be appropriate to use a recirculating chiller to reduce water and drainage costs. The chiller capacity will depend on whether cooling is required for the magnet alone or magnet and power supply. For the Model 5403 Electromagnet alone a suitable chiller is the Bay Voltex model: RRS-0550.

For recirculating cooling systems use distilled or deionized water with a biocide to prevent bacterial growth and corrosion. Do not use corrosion inhibitors in high quality electrical systems since the water conductivity is increased which can result in increased leakage currents and electrochemical corrosion.

Cooling - continued

At currents of approximately 20A and below the Model 5403 can be operated safely without water cooling. However the coil temperature will vary with the power dissipation. This results in dimensional changes of the magnet yoke and air cooling is not suitable when high field stability is required.

Freon, oil, ethylene glycol or other cooling mediums can be used. The flow required will be approximately inversely proportional to their specific heats. An experimental determination of the flow and pressure required will be necessary.

Avoid cooling the magnet below the dew point of the ambient air. Condensation may cause electrical shorts and corrosion.

During operation the resistance can be checked using a voltmeter across each coil. The voltage will rise to a constant value once thermal equilibrium has been reached. If it is desired to save water, the flow can be reduced until the hot resistance is approached. NOTE: This adjustment must be made slowly enough to allow for the thermal inertia of the coils.

Section 4

OPERATION

General

The magnet operates as a conventional electromagnet.

1. Adjust the poles to the desired gap with the poles approximately symmetrical about the center magnet line. To reduce mechanical backlash when the magnetic field is applied, it is best to set the poles by increasing the gap.
2. Adjust the cooling water flow to about 2 liters/min (0.5 USgpm) for the 5403. For operation at less than maximum power the water flow may be correspondingly reduced. Note that the inlet water temperature will determine the actual flow rate required. The above specified flow rates were determined with a water inlet temperature of approximately 18°C.
3. Turn on the power supply and increase the current until the desired field is reached.

Calibration

The induction curves may be used to estimate the field in the air gap to within four or five percent. More accurate field determination may be obtained by deriving experimentally a calibration curve for the particular pole and air gap combination being used. Magnetic hysteresis in the yoke and poles can cause an error of 30 to 70G (3 to 7mT) with an arbitrary application of such a calibration curve. This effect may be reduced to less than one percent by following a prescribed 'current setting schedule' designed to make the magnet 'forget' its prior magnetic history. The schedule should of course be used both in establishing the calibration curve and in its subsequent use. A possible schedule would be:

From zero current, increase to maximum current and reduce again to zero current. Increase again to maximum current and reduce to the current to give the desired field setting. Approaching the desired field from a higher setting will typically produce better field uniformity. This is because the field changes at the pole edges will normally lag the field change at the center thereby helping to compensate the radial decrease in field.

Greater precision in setting up the calibration curve will be achieved with the use of a digital teslameter and by making a numerical table. This table used with an interpolation routine will eliminate the error associated with reading a graph.

In any event, three points need to be remembered:

1. A calibration curve or table is only as good as the precision employed in generating it.
2. The field is defined only at the point it is measured. It will generally be different at a different point in the air gap. For example, the induction curves refer to the field on the pole axis and at the center of the air gap (median plane).
3. The field is most directly a function of the current in the magnet coils. Voltage across the coils is not a good measure of field since the electrical resistance of the coils depends on the temperature (about 0.4% per degree celsius).

Section 4

OPERATION

Field Control Operation

The necessity to use calibration curves can be avoided by using a field controller to sense the magnetic field and provide a corresponding power supply control signal through the power supply programming inputs. Contact GMW for suitable instrumentation.

Section 5

MAINTENANCE

Periodically check that the pole adjustment mechanism is clean, properly lubricated and free of grit and dirt, which may cause binding of the mechanism. Be very careful not to damage the relatively soft pole surface since this may degrade the magnetic field uniformity in the gap.

Note that the surface treatments used provide good corrosion protection but in order to maintain the inherent mechanical precision of the magnet, heavy build-up of plating materials is deliberately avoided. As a result, high humidity or otherwise seriously corrosive atmospheres can cause corrosion. Periodically apply an appropriate corrosion protection, particularly when the magnet is stored for an extended period.

Check the cooling water circuit to ensure the water is clean and free of debris and bacterial growth. Ensure the in-line water filter is clean.


Section 6

STANDARD OPTIONS


PROPRIETARY
INFORMATION
THIS DRAWING IS THE PROPERTY OF
GMW. IT IS TO BE USED ONLY FOR THE
PURPOSES SPECIFIED HEREIN. IT IS NOT
TO BE REPRODUCED OR TRANSMITTED
IN ANY FORM OR BY ANY MEANS,
ELECTRONIC OR MECHANICAL, INCLUDING
PHOTOCOPYING, RECORDING, OR BY ANY
INFORMATION STORAGE AND RETRIEVAL
SYSTEM, WITHOUT PERMISSION IN WRITING
BY GMW INC.

TOP VIEW


NOTE: ROTATING BASE SHOWN AT THE 180° POSITION



FRONT VIEW



UNDERNEATH VIEW



STEPPER MOTOR
ELECTRICAL CONNECTIONS

SIDE VIEW

MECHANICAL STOPS

HOMING MICROSWITCH CO DEEG POSITIONING

DISENGAGE LEVER RELEASES MOTOR DRIVE

RELEASE PINS USED TO REMOVE MOTOR DRIVE ASSY
FROM ROLLING/ROTATING BASE ASSY

55 (2.11)
SPOOL CLEARANCE

135 (5.31)
SERVICE ACCESS




NOTE: ROTATING BASE SHOWN AT THE 180° POSITION

ITEM		DO NOT SCALE	REVISIONS
ITEM	DESCRIPTION	DATE	BY
1	11900800	11/1/00	GMW
2	11900801	11/1/00	GMW
3	11900802	11/1/00	GMW
4	11900803	11/1/00	GMW
5	11900804	11/1/00	GMW
6	11900805	11/1/00	GMW
7	11900806	11/1/00	GMW
8	11900807	11/1/00	GMW
9	11900808	11/1/00	GMW
10	11900809	11/1/00	GMW
11	11900810	11/1/00	GMW
12	11900811	11/1/00	GMW
13	11900812	11/1/00	GMW

ITEM	DESCRIPTION	DATE	BY
1	11900800	11/1/00	GMW
2	11900801	11/1/00	GMW
3	11900802	11/1/00	GMW
4	11900803	11/1/00	GMW
5	11900804	11/1/00	GMW
6	11900805	11/1/00	GMW
7	11900806	11/1/00	GMW
8	11900807	11/1/00	GMW
9	11900808	11/1/00	GMW
10	11900809	11/1/00	GMW
11	11900810	11/1/00	GMW
12	11900811	11/1/00	GMW
13	11900812	11/1/00	GMW


ITEM	DESCRIPTION	DATE	BY
1	11900800	11/1/00	GMW
2	11900801	11/1/00	GMW
3	11900802	11/1/00	GMW
4	11900803	11/1/00	GMW
5	11900804	11/1/00	GMW
6	11900805	11/1/00	GMW
7	11900806	11/1/00	GMW
8	11900807	11/1/00	GMW
9	11900808	11/1/00	GMW
10	11900809	11/1/00	GMW
11	11900810	11/1/00	GMW
12	11900811	11/1/00	GMW
13	11900812	11/1/00	GMW

ITEM	DESCRIPTION	DATE	BY
1	11900800	11/1/00	GMW
2	11900801	11/1/00	GMW
3	11900802	11/1/00	GMW
4	11900803	11/1/00	GMW
5	11900804	11/1/00	GMW
6	11900805	11/1/00	GMW
7	11900806	11/1/00	GMW
8	11900807	11/1/00	GMW
9	11900808	11/1/00	GMW
10	11900809	11/1/00	GMW
11	11900810	11/1/00	GMW
12	11900811	11/1/00	GMW
13	11900812	11/1/00	GMW




NOTE:

- 1 INSTALL LABEL [ITEM 12] ONTO LOCK HOUSING [ITEM 4].
THEN TRIM AROUND CUTOFF FOR RELEASE PINS.
- 2 APPLY LOCOTTE TO THREADS ON [ITEM 24].
THEN ASSEMBLE LOCK HOUSING [ITEM 4],
USING S/S SPACER [ITEM 10].
- 3 SCREW DOWN [ITEM 14] SO THAT [ITEM 6]
IS RETAINED IN BOTH DETENTS.
LOOK IN PLACE WITH [ITEM 39].
- 4 FIT [ITEM 44] OVER EXPOSED AREA OF [ITEM 17]




REVISIONS			
REV	DESCRIPTION	DATE	APPROVED
A	RELEASE	07/07/07	CLINICAL
B	ADD ITEM 4.3.4, CHG NOTES, ITEM 13	11/29/07	BUDHRAJ
C	CHG ITEM 1.3.4.4, ADD NOTE 4	04/07/08	BUDHRAJ

[illegible]



DETAIL "B"



ZERO BUTT®



BOTTOM VIEW

ITEM	QTY	PART NUMBER	DESCRIPTION
1	18	1 1010D170	LABEL, SPDOL, IDENTIFICATION
2	1	2 BN 782	WASHER, FLAT M6 X 1.6 S/S
3	1	10DN 1267	NUT, HEX BORED M6 X 12 S/S
4	5	4 BN 782	WASHER, LOCK M6 X 1.2
5	14	65 BN 792	WASHER, LOCK M6 X 1.4
6	13	1 B800	BOLT, M6 X 16 HEX NUTLN
7	12	65 DN 912	SHCS M6 X 16 S/S
8	11	4 DN 612	SHCS M6 X 25 S/S
9	10	2 DN 913 A2	SHSS M6 X 10 S/S
10	6	2 DN 913 A2	SHSS M6 X 12 S/S
11	6	1010M	PANNO WIRE 5/5
12	7	1 DN 6225	DOVEL PIN, M6 X 60
13	6	1 179011000	STOP BAR
14	5	1 179011100	STOP BAR GUIDE
15	4	6 55M4-1IN	BALL PLUNGER, VIER 5/5
16	3	1 179011-30	SPDOL CLAMP RING
17	2	1 12900920	WORN GEAR, BRONZE
18	1	1 11800630	SPDOL WELDED ASSY
PARTS LIST			DESCRIPTION
NOTE			

GMW

P.O. Box 2578, Redwood City, CA 94064
Tel: (650)802-8292 Fax: (650)802-8298

FILE
MOTORIZED.ROT.DRIVE
SPOOL ASSEMBLY


A1 1900820

SOFTWARE
AUTOCAD 13

SCALE 1/2" = 1'	IN	FEET
-----------------	----	------

PROPRIETARY
THIS DRAWING CONTAINS CONFIDENTIAL INFORMATION
PROPRIETARY TO GDMV, INC. IT MUST NOT BE
REPRODUCED OR DISCLOSED TO OTHERS OR USED IN ANY
MANNER THAT VIOLATES THE PATENT RIGHTS OF GDMV, INC.
OR ANY OTHER PARTY. GDMV, INC. IS NOT RESPONSIBLE FOR
ANY REPRODUCTION OR USE OF THIS DRAWING IN ANY
MANNER WITHOUT THE WRITTEN PERMISSION OF GDMV, INC.

REVISIONS			
REV	DESCRIPTION	DRAWN	DATE
A	RELEASE		07/07/97 G.DOUGLAS



BOTTOM VIEW

REAR VIEW

TOP VIEW

PARTS LIST

ITEM	QTY	PART NUMBER	DESCRIPTION	NOTE
10	6	BN 752	WASHER, LOCK SP/S M2 X 0.5 SP/S	
9	6	BN 792	WASHER, LOCK SP/S M3 X 0.9 SP/S	
8	6	DN 912	BOLT, SHCS M2 X 10 S/S	
7	6	DN 912	BOLT, SHCS M3 X 10 S/S	
6	2	V4NT7	MICROSWTCH, BURGESS	
5	1	V4NT9	MICROSWTCH, BURGESS	
4	1	17901170	SHAFT, ZERO MICROSWTCH	
3	2	17901160	BRACKET, LIMIT MICROSWTCH	
2	1	17901150	BRACKET, ZERO MICROSWTCH	
1	1	17901070	STOP BLOCK	

DRAWN
G. DOUGLAS
05/02/97

CHECK
DATE

ENGINEERING
DATE

DO NOT SCALE
FROM DRAWING
DIMENSIONS & TOLERANCES
ARE AS SHOWN UNLESS OTHERWISE SPECIFIED

LINEAR
DIMENSIONS
mm

ANGULAR
DIMENSIONS
deg

FINISH
1.6

THIRD ANGLE PROJECTION

GMV
P.O. Box 2578, Redwood City, CA 94064
Tel: (650)802-8292. Fax: (650)802-8298.

**MOTORIZED.ROT.DRIVE
STOP BLOCK ASSY**

SIZE
A2 11900840

SCALE 1:1

WT kg


SHEET 1 OF 1

REV
A

DRAWING NO.
11900840

REV
A

PROPRIETARY



TOP VIEW

FRONT VIEW

NOTE:

1. USE ITEM 11 TO PACK WORM DRIVE ASSEMBLY TO REDUCE SHAFT AXIAL MOVEMENT TO MINIMUM POSSIBLE. SHAFT MUST ROTATE FREELY.

REVISONS			
REV	DESCRIPTION	DRAFT	DATE APPROVED
A	RELEASE		01/07/97 G.DUIGLAS
B	ADD ITEM 11 AND NOTE: 1, CH6 ITEM 3		11/27/97 G.DUIGLAS
C	CH6 ITEM 3		04/09/98 G.DUIGLAS

11A/R	BN 74B	SHIM WASHER, 14 X 26 X 0.1MM THICK		
10	1 DIN 1481	PN, SPRING, M4 X 2BL SP/S		
9	1 DIN 1481	PN, SPRING M4 X 1BL SP/S		
8	2 BR5-3	BEARING, THRUST, BERG		
7	4 A 902B-68	RETAINING RING [ORCLP], SDP		
6	2 S89NH2-BN162	BEARING, NEEDLE ROLLER, SDP		
5	2 17901190	SPACER, WORM		
4	1 12900060	WORM SHAFT		
3	1 12900041	PULLEY, 18 TEETH [FOR 1/2" SHAFT]		
2	1 12900030	WORM		
1	1 17901080	WORM MOUNT		
ITEM	QTY	PART NUMBER	DESCRIPTION	NOTES

GMW
P.O. Box 2578, Redwood City, CA 94064
Tel: (650)802-8292. Fax: (650)802-8298.


MOTORIZED.ROT.DRIVE
WORM MOUNT ASSY

11900850 A2

SCALE 1:1	WT kg	SHEET 1 OF 1
-----------	-------	--------------

PROPOSED BY: **GMW**
DESIGNED BY: **GMW**
CHECKED BY: **GMW**
APPROVED BY: **GMW**
DATE: 02/11/00



TOP VIEW



MOTOR AND LIMIT SWITCH CABLE PART NO 16900400

SERIAL COMMUNICATIONS CABLE PART NO 16900410


AC POWER INPUT



REV	DESCRIPTION	SHEET	DATE	APPROVED
A	RELEASE	02/11/00	02/11/00	GMW

ITEM	QTY	PART NUMBER	DESCRIPTION	NOTE
1	1	GMW	DO NOT SCALE	
2	1	GMW	DO NOT SCALE	
3	1	GMW	DO NOT SCALE	
4	1	GMW	DO NOT SCALE	
5	1	GMW	DO NOT SCALE	
6	1	GMW	DO NOT SCALE	
7	1	GMW	DO NOT SCALE	
8	1	GMW	DO NOT SCALE	
9	1	GMW	DO NOT SCALE	
10	1	GMW	DO NOT SCALE	
11	1	GMW	DO NOT SCALE	
12	1	GMW	DO NOT SCALE	
13	1	GMW	DO NOT SCALE	
14	1	GMW	DO NOT SCALE	
15	1	GMW	DO NOT SCALE	
16	1	GMW	DO NOT SCALE	
17	1	GMW	DO NOT SCALE	
18	1	GMW	DO NOT SCALE	
19	1	GMW	DO NOT SCALE	
20	1	GMW	DO NOT SCALE	
21	1	GMW	DO NOT SCALE	
22	1	GMW	DO NOT SCALE	
23	1	GMW	DO NOT SCALE	
24	1	GMW	DO NOT SCALE	
25	1	GMW	DO NOT SCALE	
26	1	GMW	DO NOT SCALE	
27	1	GMW	DO NOT SCALE	
28	1	GMW	DO NOT SCALE	
29	1	GMW	DO NOT SCALE	
30	1	GMW	DO NOT SCALE	
31	1	GMW	DO NOT SCALE	
32	1	GMW	DO NOT SCALE	
33	1	GMW	DO NOT SCALE	
34	1	GMW	DO NOT SCALE	
35	1	GMW	DO NOT SCALE	
36	1	GMW	DO NOT SCALE	
37	1	GMW	DO NOT SCALE	
38	1	GMW	DO NOT SCALE	
39	1	GMW	DO NOT SCALE	
40	1	GMW	DO NOT SCALE	
41	1	GMW	DO NOT SCALE	
42	1	GMW	DO NOT SCALE	
43	1	GMW	DO NOT SCALE	
44	1	GMW	DO NOT SCALE	
45	1	GMW	DO NOT SCALE	
46	1	GMW	DO NOT SCALE	
47	1	GMW	DO NOT SCALE	
48	1	GMW	DO NOT SCALE	
49	1	GMW	DO NOT SCALE	
50	1	GMW	DO NOT SCALE	
51	1	GMW	DO NOT SCALE	
52	1	GMW	DO NOT SCALE	
53	1	GMW	DO NOT SCALE	
54	1	GMW	DO NOT SCALE	
55	1	GMW	DO NOT SCALE	
56	1	GMW	DO NOT SCALE	
57	1	GMW	DO NOT SCALE	
58	1	GMW	DO NOT SCALE	
59	1	GMW	DO NOT SCALE	
60	1	GMW	DO NOT SCALE	
61	1	GMW	DO NOT SCALE	
62	1	GMW	DO NOT SCALE	
63	1	GMW	DO NOT SCALE	
64	1	GMW	DO NOT SCALE	
65	1	GMW	DO NOT SCALE	
66	1	GMW	DO NOT SCALE	
67	1	GMW	DO NOT SCALE	
68	1	GMW	DO NOT SCALE	
69	1	GMW	DO NOT SCALE	
70	1	GMW	DO NOT SCALE	
71	1	GMW	DO NOT SCALE	
72	1	GMW	DO NOT SCALE	
73	1	GMW	DO NOT SCALE	
74	1	GMW	DO NOT SCALE	
75	1	GMW	DO NOT SCALE	
76	1	GMW	DO NOT SCALE	
77	1	GMW	DO NOT SCALE	
78	1	GMW	DO NOT SCALE	
79	1	GMW	DO NOT SCALE	
80	1	GMW	DO NOT SCALE	
81	1	GMW	DO NOT SCALE	
82	1	GMW	DO NOT SCALE	
83	1	GMW	DO NOT SCALE	
84	1	GMW	DO NOT SCALE	
85	1	GMW	DO NOT SCALE	
86	1	GMW	DO NOT SCALE	
87	1	GMW	DO NOT SCALE	
88	1	GMW	DO NOT SCALE	
89	1	GMW	DO NOT SCALE	
90	1	GMW	DO NOT SCALE	
91	1	GMW	DO NOT SCALE	
92	1	GMW	DO NOT SCALE	
93	1	GMW	DO NOT SCALE	
94	1	GMW	DO NOT SCALE	
95	1	GMW	DO NOT SCALE	
96	1	GMW	DO NOT SCALE	
97	1	GMW	DO NOT SCALE	
98	1	GMW	DO NOT SCALE	
99	1	GMW	DO NOT SCALE	
100	1	GMW	DO NOT SCALE	

MOTOR DRIVE ASSEMBLY
PART NO: 11900800/1




- NOTE:
- 1 USE BLACK WIRES FROM GREEN AND WHITE PAIRS. DO NOT MIX WITH BLACK WIRES USED FOR STEPPER MOTOR.
 2. HOMING SWITCH USES NORMALLY OPEN CONTACT. LIMIT SWITCHES USE NORMALLY CLOSED CONTACTS.


[illegible]

PROPRIETARY
THIS DRAWING CONTAINS CONFIDENTIAL INFORMATION
PROPRIETARY TO GDMW INC. IT MUST NOT BE
REPRODUCED OR DISCLOSED TO OTHERS OR USED IN ANY
MANNER WITHOUT THE EXPRESS WRITTEN PERMISSION
OF GDMW INC.

REVISIONS			
REV	DESCRIPTION	DRAWN	DATE
A	RELEASE	08/11/98	G.DOUGLAS



MAGNET MODEL	INSTALLATION POSITION	ASSEMBLY NUMBER	VERTICAL TRAVEL "mm"	HORIZONTAL TRAVEL "mm"
3474	REAR	11901251	280mm	200mm
3474	FRONT	11901252	280mm	100mm
3473	REAR	11901261	180mm	150mm
3473	FRONT	11901262	180mm	40mm
3472	REAR	11901271	130mm	100mm
3472	FRONT	11901272	130mm	30mm
5403	BOTH	11901280	130mm	100mm
3470	BOTH	11901290	130mm	100mm



- TO SET HUB TO DESIRED ANGLE
- 1 LOOSEN THUMB NUT 2mm
 - 2 PULL HUB FORWARD 2mm
 - 3 ROTATE TO ANGLE REQUIRED
 - 4 ROTATE SLIGHTLY BACK AND FORTH TO FIND INDEX PIN
 - 5 PUSH HUB REARWARDS
 - 6 TIGHTEN THUMB NUTS

ITEM	QTY	PART NUMBER	DESCRIPTION	NOTE
PARTS LIST				
DRAWN G.DOUGLAS 08/11/98				
CHECK DATE				
DO NOT SCALE FROM DRAWING				
DIMENSIONS & TOLERANCES ARE IN MILLIMETERS UNLESS OTHERWISE SPECIFIED				
ENGINEERING DATE				
LAYER THICKNESS / mm				
X.XXX 4.00 44.03				
X.X 4.0 44.1				
X.X 5.03 44.3				
X 5.08 44.3				
DES 5.5 44.5				
FINISH 6.3 44.6				
NICK ASSY SYSTEM THIRD ANGLE PROJECTION				
SOFTWARE AUTOCAD 13				
SCALE 1:1 WT KG SHEET 1 OF 1				
REV A				

PROBE MOUNT
GENERAL ASSEMBLY

NOTE: ABOVE PROBE MOUNT SHOWN INSTALLED ON MODEL 3474 ELECTROMAGNET.
OTHER CONFIGURATIONS AND MOUNTINGS ARE AVAILABLE. CONSULT TABLE FOR GDMW ELECTROMAGNETS.


SIZE	DRAWING NO.	REV
A2	11901280	A
SCALE 1:1	WT kg	SHEET 1 OF 1

Section 7

CUSTOM OPTIONS

PROPRIETARY
THIS DRAWING CONTAINS CONFIDENTIAL INFORMATION
PROPERTY OF GMW INC. IT SHALL NOT BE
REPRODUCED OR DISCLOSED TO OTHERS OR USED IN ANY
MANNER THAT IS IN VIOLATION OF THE PATENT RIGHTS
OF GMW INC.

REVISIONS				
REV	DESCRIPTION	DRAFT	DATE	APPROVED
A	RELEASE		04/19/95	G.DOUGLAS
B	CHANGE LH POLE TO STEPPED DRILLED HOLE		08/31/95	G.DOUGLAS



POLE GAP SPACER RING
DWG NO 17900290


NOTE:

- ① POLE WITH HOLE 11mm AT FACE AND 8° CLEARANCE ANGLE
SEE DWG 17612621 FOR DETAILS
- ② POLE WITH HOLE 6mm AT FACE
SEE DWG 17612622 FOR DETAILS

ITEM	QTY	PART NUMBER	DESCRIPTION	NOTE
PARTS LIST				
DRAWN G.DOUGLAS	DATE	DO NOT SCALE FROM DRAWING		
CHECK	DATE	DIMENSIONS & TOLERANCES UNLESS OTHERWISE SPECIFIED		
ENGINEERING	DATE	UNLESS OTHERWISE SPECIFIED		
		UNITS	INCHES	MM
		1/16"	1/32"	0.031
		1/8"	1/16"	0.062
		3/16"	3/32"	0.094
		1/2"	1/8"	0.125
		5/8"	3/16"	0.188
		3/4"	1/2"	0.250
		7/8"	7/16"	0.312
		1"	1"	0.375
		1 1/4"	1 1/4"	0.438
		1 1/2"	1 1/2"	0.500
		2"	2"	0.562
		2 1/2"	2 1/2"	0.625
		3"	3"	0.688
		3 1/2"	3 1/2"	0.750
		4"	4"	0.812
		4 1/2"	4 1/2"	0.875
		5"	5"	0.938
		5 1/2"	5 1/2"	1.000
		6"	6"	1.062
		6 1/2"	6 1/2"	1.125
		7"	7"	1.188
		7 1/2"	7 1/2"	1.250
		8"	8"	1.312
		8 1/2"	8 1/2"	1.375
		9"	9"	1.438
		9 1/2"	9 1/2"	1.500
		10"	10"	1.562
		10 1/2"	10 1/2"	1.625
		11"	11"	1.688
		11 1/2"	11 1/2"	1.750
		12"	12"	1.812
		12 1/2"	12 1/2"	1.875
		13"	13"	1.938
		13 1/2"	13 1/2"	2.000
		14"	14"	2.062
		14 1/2"	14 1/2"	2.125
		15"	15"	2.188
		15 1/2"	15 1/2"	2.250
		16"	16"	2.312
		16 1/2"	16 1/2"	2.375
		17"	17"	2.438
		17 1/2"	17 1/2"	2.500
		18"	18"	2.562
		18 1/2"	18 1/2"	2.625
		19"	19"	2.688
		19 1/2"	19 1/2"	2.750
		20"	20"	2.812
		20 1/2"	20 1/2"	2.875
		21"	21"	2.938
		21 1/2"	21 1/2"	3.000
		22"	22"	3.062
		22 1/2"	22 1/2"	3.125
		23"	23"	3.188
		23 1/2"	23 1/2"	3.250
		24"	24"	3.312
		24 1/2"	24 1/2"	3.375
		25"	25"	3.438
		25 1/2"	25 1/2"	3.500
		26"	26"	3.562
		26 1/2"	26 1/2"	3.625
		27"	27"	3.688
		27 1/2"	27 1/2"	3.750
		28"	28"	3.812
		28 1/2"	28 1/2"	3.875
		29"	29"	3.938
		29 1/2"	29 1/2"	4.000
		30"	30"	4.062
		30 1/2"	30 1/2"	4.125
		31"	31"	4.188
		31 1/2"	31 1/2"	4.250
		32"	32"	4.312
		32 1/2"	32 1/2"	4.375
		33"	33"	4.438
		33 1/2"	33 1/2"	4.500
		34"	34"	4.562
		34 1/2"	34 1/2"	4.625
		35"	35"	4.688
		35 1/2"	35 1/2"	4.750
		36"	36"	4.812
		36 1/2"	36 1/2"	4.875
		37"	37"	4.938
		37 1/2"	37 1/2"	5.000
		38"	38"	5.062
		38 1/2"	38 1/2"	5.125
		39"	39"	5.188
		39 1/2"	39 1/2"	5.250
		40"	40"	5.312
		40 1/2"	40 1/2"	5.375
		41"	41"	5.438
		41 1/2"	41 1/2"	5.500
		42"	42"	5.562
		42 1/2"	42 1/2"	5.625
		43"	43"	5.688
		43 1/2"	43 1/2"	5.750
		44"	44"	5.812
		44 1/2"	44 1/2"	5.875
		45"	45"	5.938
		45 1/2"	45 1/2"	6.000
		46"	46"	6.062
		46 1/2"	46 1/2"	6.125
		47"	47"	6.188
		47 1/2"	47 1/2"	6.250
		48"	48"	6.312
		48 1/2"	48 1/2"	6.375
		49"	49"	6.438
		49 1/2"	49 1/2"	6.500
		50"	50"	6.562
		50 1/2"	50 1/2"	6.625
		51"	51"	6.688
		51 1/2"	51 1/2"	6.750
		52"	52"	6.812
		52 1/2"	52 1/2"	6.875
		53"	53"	6.938
		53 1/2"	53 1/2"	7.000
		54"	54"	7.062
		54 1/2"	54 1/2"	7.125
		55"	55"	7.188
		55 1/2"	55 1/2"	7.250
		56"	56"	7.312
		56 1/2"	56 1/2"	7.375
		57"	57"	7.438
		57 1/2"	57 1/2"	7.500
		58"	58"	7.562
		58 1/2"	58 1/2"	7.625
		59"	59"	7.688
		59 1/2"	59 1/2"	7.750
		60"	60"	7.812
		60 1/2"	60 1/2"	7.875
		61"	61"	7.938
		61 1/2"	61 1/2"	8.000
		62"	62"	8.062
		62 1/2"	62 1/2"	8.125
		63"	63"	8.188
		63 1/2"	63 1/2"	8.250
		64"	64"	8.312
		64 1/2"	64 1/2"	8.375
		65"	65"	8.438
		65 1/2"	65 1/2"	8.500
		66"	66"	8.562
		66 1/2"	66 1/2"	8.625
		67"	67"	8.688
		67 1/2"	67 1/2"	8.750
		68"	68"	8.812
		68 1/2"	68 1/2"	8.875
		69"	69"	8.938
		69 1/2"	69 1/2"	9.000
		70"	70"	9.062
		70 1/2"	70 1/2"	9.125
		71"	71"	9.188
		71 1/2"	71 1/2"	9.250
		72"	72"	9.312
		72 1/2"	72 1/2"	9.375
		73"	73"	9.438
		73 1/2"	73 1/2"	9.500
		74"	74"	9.562
		74 1/2"	74 1/2"	9.625
		75"	75"	9.688
		75 1/2"	75 1/2"	9.750
		76"	76"	9.812
		76 1/2"	76 1/2"	9.875
		77"	77"	9.938
		77 1/2"	77 1/2"	10.000
		78"	78"	10.062
		78 1/2"	78 1/2"	10.125
		79"	79"	10.188
		79 1/2"	79 1/2"	10.250
		80"	80"	10.312
		80 1/2"	80 1/2"	10.375
		81"	81"	10.438
		81 1/2"	81 1/2"	10.500
		82"	82"	10.562
		82 1/2"	82 1/2"	10.625
		83"	83"	10.688
		83 1/2"	83 1/2"	10.750
		84"	84"	10.812
		84 1/2"	84 1/2"	10.875
		85"	85"	10.938
		85 1/2"	85 1/2"	11.000
		86"	86"	11.062
		86 1/2"	86 1/2"	11.125
		87"	87"	11.188
		87 1/2"	87 1/2"	11.250
		88"	88"	11.312
		88 1/2"	88 1/2"	11.375
		89"	89"	11.438
		89 1/2"	89 1/2"	11.500
		90"	90"	11.562
		90 1/2"	90 1/2"	11.625
		91"	91"	11.688
		91 1/2"	91 1/2"	11.750
		92"	92"	11.812
		92 1/2"	92 1/2"	11.875
		93"	93"	11.938
		93 1/2"	93 1/2"	12.000
		94"	94"	12.062
		94 1/2"	94 1/2"	12.125
		95"	95"	12.188
		95 1/2"	95 1/2"	12.250
		96"	96"	12.312
		96 1/2"	96 1/2"	12.375
		97"	97"	12.438
		97 1/2"	97 1/2"	12.500
		98"	98"	12.562
		98 1/2"	98 1/2"	12.625
		99"	99"	12.688
		99 1/2"	99 1/2"	12.750
		100"	100"	12.812
		100 1/2"	100 1/2"	12.875
		101"	101"	12.938
		101 1/2"	101 1/2"	13.000
		102"	102"	13.062
		102 1/2"	102 1/2"	13.125
		103"	103"	13.188
		103 1/2"	103 1/2"	13.250
		104"	104"	13.312
		104 1/2"	104 1/2"	13.375
		105"	105"	13.438
		105 1/2"	105 1/2"	13.500
		106"	106"	13.562
		106 1/2"	106 1/2"	13.625
		107"	107"	13.688
		107 1/2"	107 1/2"	13.750
		108"	108"	13.812
		108 1/2"	108 1/2"	13.875
		109"	109"	13.938
		109 1/2"	109 1/2"	14.000
		110"	110"	14.062
		110 1/2"	110 1/2"	14.125
		111"	111"	14.188
		111 1/2"	111 1/2"	14.250
		112"	112"	14.312
		112 1/2"	112 1/2"	14.375
		113"	113"	14.438
		113 1/2"	113 1/2"	14.500
		114"	114"	14.562
		114 1/2"	114 1/2"	14.625
		115"	115"	14.688
		115 1/2"	115 1/2"	14.750
		116"	116"	14.812
		116 1/2"	116 1/2"	14.875
		117"	117"	14.938
		117 1/2"	117 1/2"	15.000
		118"	118"	15.062
		118 1/2"	118 1/2"	15.125
		119"	119"	15.188
		119 1/2"	119 1/2"	15.250
		120"	120"	15.312
		120 1/2"	120 1/2"	15.375
		121"	121"	15.438
		121 1/2"	121 1/2"	15.500
		122"	122"	15.562
		122 1/2"	122 1/2"	15.625
		123"	123"	15.688
		123 1/2"	123 1/2"	15.750
		124"	124"	15.812
		124 1/2"	124 1/2"	15.875
		125"	125"	15.938
		125 1/2"	125 1/2"	16.000
		126"	126"	16.062
		126 1/2"	126 1/2"	16.125
		127"	127"	16.188
		127 1/2"	127 1/2"	16.250
		128"	128"	16.312
		128 1/2"	128 1/2"	16.375
		129"	129"	16.438

PROPRIETARY
THIS DRAWING CONTAINS CONFIDENTIAL INFORMATION
PROPRIETARY TO GMW INC. IT MUST NOT BE
REPRODUCED OR DISCLOSED TO OTHERS OR USED IN ANY
OTHER WAY, IN WHOLE OR IN PART EXCEPT AS AUTHORIZED
IN WRITING BY GMW INC.

REVISIONS				
REV	DESCRIPTION	DRAFT	DATE	APPROVED
A	RELEASE		05/17/95	G.DOUGLAS
B	CHANGE TO STEPPED DRILLED HOLE		06/17/95	G.DOUGLAS



NOTES


1. ADD MACHINED DETAILS ABOVE TO MODEL: 5403 POLE
DRAWING NO: 17612620
2. AVOID NICKS SCRATCHS AND MACHINING MARKS
ON THE POLE FACE AND OUTER SURFACES

ITEM	QTY	PART NUMBER	DESCRIPTION	NOTE
PARTS LIST				
DRAWN G.DOUGLAS	DATE 04/18/95	DO NOT SCALE FROM DRAWING DIMENSIONS & TOLERANCES (UNLESS OTHERWISE SPECIFIED)		
CHECK	DATE			
ENGINEERING	DATE			
		LINEAR	INCHES	mm
		X.XXX	±.009	±0.03
		X.XX	±.01	±0.1
		X.X	±.03	±0.3
		X	±.06	±1
		DEC.	±.5	±0.5
		FINISH	63	1.6
NEXT ASSY	SYSTEM	THIRD ANGLE PROJECTION		
SOFTWARE: AUTOCAD 12				
TITLE		SIZE	DRAWING NO.	REV
GMW P.O. Box 2578, Redwood City, CA 94064 Tel: (415)802-8292 Fax: (415)802-8298.		A2	17612621	B
SCALE 1:1		WT kg	SHEET 1	OF 1

PROPRIETARY

THIS DRAWING CONTAINS CONFIDENTIAL INFORMATION PROPRIETARY TO GMW INC. IT MUST NOT BE REPRODUCED OR DISCLOSED TO OTHERS OR USED IN ANY OTHER WAY, IN WHOLE OR IN PART EXCEPT AS AUTHORIZED IN WRITING BY GMW INC.

REVISIONS				
REV	DESCRIPTION	DRAFT	DATE	APPROVED
A	RELEASE		04/18/95	G.DOUGLAS




ADD 6mm [0.236] HOLE AT POLE FACE
BREAK HOLE EDGE 0.1mm

— ORIGINAL POLE MACHINED DETAILS

NOTES


1. ADD MACHINED DETAILS ABOVE TO MODEL: 5403 POLE
DRAWING NO 1761260
2. AVOID NICKS SCRATCHS AND MACHINING MARKS
ON THE POLE FACE AND OUTER SURFACES


ITEM		QTY		PART NUMBER		DESCRIPTION		NOTE	
PARTS LIST									
DRAWN G.DOUGLAS		DATE 04/18/95		DO NOT SCALE FROM DRAWING DIMENSIONS & TOLERANCES (UNLESS OTHERWISE SPECIFIED)		GMW 955 Industrial Rd, San Carlos, CA 94070 Tel: (650)802-8292. Fax: (650)802-8298.			
CHECK		DATE							
ENGINEERING		DATE							
				LINEAR X.XXX ± 0.00 mm X.XX ± 0.1 X.X ± 0.3 X ± 0.6 DEG. ± 5 FINISH $63 \sqrt{1.6}$		TITLE POLE: CYLINDRICAL MODEL: 5403			
5403				SIZE		DRAWING NO.		REV	
NEXT ASSY		SYSTEM		THIRD ANGLE PROJECTION		A2 17612622		A	
SOFTWARE AUTOCAD 13						SCALE 1:1 WT kg		SHEET 1 OF 1	

REVISIONS				
REV	DESCRIPTION	DRAFT	DATE	APPROVED
A	RELEASE		11/20/96	G.DOUGLAS




1. MATERIAL CARBON STEEL
2. FINISH E.N PLATE 0.01 THICK
3. QUANTITY OF 2 RINGS PER MAGNET NEEDED.
4. DRAWING SHOWS DIMENSIONS BEFORE PLATING

ITEM	QTY	PART NUMBER	DESCRIPTION		NOTE
PARTS LIST					
DRAWN G.DOUGLAS		DATE 11/20/96	DO NOT SCALE FROM DRAWING DIMENSIONS & TOLERANCES (UNLESS OTHERWISE SPECIFIED)		
CHECK		DATE	<div> <div> <div>GMW</div> <div>P.O. Box 2578, Redwood City, CA 94064</div> <div>Tel: (415)802-8292 Fax: (415)802-8298.</div> </div> <div> <div>TITLE</div> <div>POLE SPACER RING</div> <div>MODEL: 5403</div> </div> </div>		
ENGINEERING		DATE	<div> <div>LINEAR</div> <div>INCHES/mm</div> <div> <div>X.XXX ±.005</div> <div>±0.03</div> </div> </div>		
			<div> <div>X.XX ±.01</div> <div>±0.1</div> </div>		
			<div> <div>X.X ±.03</div> <div>±0.3</div> </div>		
			<div> <div>X ±.06</div> <div>±1</div> </div>		
			<div> <div>DEG. ±.5</div> <div>±0.5</div> </div>		
			<div> <div>FINISH</div> <div>63 ✓ 1.6 ✓</div> </div>		
NEXT ASSY		SYSTEM	SIZE		REV
			DRAWING NO.		
SOFTWARE: AUTOCAD 13		THIRD ANGLE PROJECTION	A2 17900290-20		A
			SCALE 1:1 WT kg		SHEET 1 OF 1



FRONT VIEW



SIDE VIEW

PROPRIETARY
This document contains information proprietary to GMW Inc. It must not be reproduced or disclosed to others or used in any other way, in whole or part, except as authorized in writing by GMW Inc.

MAGNETIC PLOTTING AXIS

809000040

A

SHEET 1 OF 1

GMW ASSOCIATES

LABORATORY ELECTROMAGNET UNIFORMITY PLOT

Model 5403
Serial No 42


Pole Face 38 mm
Pole Gap 25 mm
Hole Dia 4mm
US Army Redstone Arsenal

Engr Toomas Rett
Date June 27, 1995

Magnet Current 50 Amps

C7915

Plot Y = 0.0 mm, Z = 0.0 mm				
X - mm	Magnet Field Tesla	X + mm	Magnet Field Tesla	Magnet Field Average Tesla
0	1.31090	0	1.31090	1.31093
-2	1.30950	2	1.30915	1.30933
-4	1.30475	4	1.30395	1.30435
-6	1.29600	6	1.29415	1.29508
-8	1.28145	8	1.27850	1.27998
-10	1.25845	10	1.25585	1.25715
-12	1.22800	12	1.22315	1.22558
-14	1.18620	14	1.18145	1.18383
-16	1.13550	16	1.12820	1.13185
-18	1.07110	18	1.07895	1.07503
-20	0.99980	20	1.01120	1.00550
0	1.31095	0	1.31090	1.31093



GMW ASSOCIATES

LABORATORY ELECTROMAGNET UNIFORMITY PLOT

Model 5403
Serial No 42


Pole Face 38 mm
Pole Gap 25 mm
Hole Dia 4mm
US Army Redstone Arsenal

Engr Toomas Rett
Date June 27, 1995

Magnet Current 50 Amps

C7915

Plot Y = 0.0 mm, Z = 0.0 mm				
X -	Magnet Field	X +	Magnet Field	Magnet Field Average
mm	Tesla	mm	Tesla	Tesla
0	1.31090	0	1.31090	1.310925
-2	1.30950	2	1.30915	1.309325
-4	1.30475	4	1.30395	1.304350
-6	1.29600	6	1.29415	1.295075
-8	1.28145	8	1.27850	1.279975
-10	1.25845	10	1.25585	1.257150
-12	1.22800	12	1.22315	1.225575
-14	1.18620	14	1.18145	1.183825
-16	1.13550	16	1.12820	1.131850
-18	1.07110	18	1.07895	1.075025
-20	0.99980	20	1.01120	1.005500
0	1.31095	0	1.31090	1.310925




Section 8

EXCITATION CURVES

GMW Associates
Electromagnet Excitation Plot
Field Vs Gap

Contract No:		Page: 1 of 1	Date: May 18, 89
Customer:			Engr: G.Douglas
Model: 5403		Power Supply:	Set Current: 50 Amps
Serial No: 12		Serial No:	Target Field:
Pole Face: As per table below		Position: X=0, Y=0, Z=0	
Serial No: None		Notes:	
Pole Gap: As per table below			
Pole Spacers: None			




GMW Associates

Electromagnet Excitation Plot


Field Vs Current

Contract No:		Page: 1 of 2	Date: May 19, 89
Customer:			Engr: G.Douglas
Model: 5403		Power Supply:	Set Current:
Serial No: 12		Serial No:	Target Field:
Pole Face: 76 mm		Position: X=0, Y=0, Z=0	
Serial No: None		Notes:	
Pole Gap: As per table below			
Pole Spacers: None			



GMW Associates
Electromagnet Excitation Plot
Field Vs Current

Contract No:		Page: 2 of 2	Date: May 19, 89
Customer:			Engr: G.Douglas
Model: 5403	Power Supply:	Set Current:	
Serial No: 12	Serial No:	Target Field:	
Pole Face: 38 mm	Position: X=0, Y=0, Z=0		
Serial No: None	Notes:		
Pole Gap: As per table below			
Pole Spacers: None			



Section 9

TEST DATA

Section 10

DRAWINGS

SERIES 3450/3450R/3455R/3455RBV 15 AMP THERMOSTATS

Typical Applications:

Power Supplies

Communication
Equipment

Medical Equipment

Computers (Where
High AMP Loads are
Present)




The Series 3450/3455R is a snap-acting, non-adjustable precision thermostat especially suited for industrial and electrical equipment.

The 3450 (.390" or 10mm overall) is ideal for applications that require precision control of high electric loads to 8 Amp resistive.

The 3450R and 3455R have a patented metal insert rivet construction.

The 3455R (.484" or 12.5mm) overall, has higher spacing as required by European approval agencies. Model 3455RBV is an epoxy overmold version of the 3455R, specifically designed for electrical insulation or protection in a high humidity environment. Consult factory for performance qualifications.

To insure that a safe combination of thermostat and application is achieved, the purchaser must determine product suitability for their individual requirements.



*Series 3450/3450R/3455R/3455RBV

MODEL	ELECTRIC LIFE CYCLES	120 VAC	240 VAC	277VAC
3450	100,000	8.0A	-	-
3450R/	100,000	15A	8.3A	7.2A
3455R	100,000	4.4FLA 25.4LRA	2.2FLA 13.2LRA	-
	6,000	5.8FLA 34.8LRA	2.9FLA 17.4LRA	-
3455RBV	100,000	15A	8.3A	-
	6,000	5.8A 34.8LRA	2.9A 17.4LRA	-

A: Amps

FLA: Full Load Amps

LRA: Locked Rotor Amps

Contacts are available for millivolt and milliamp applications.

*Includes UL and CSA ratings.

Consult Elmwood Sensors for additional ratings.

Key Features:

- Electric Rating to 15 Amp 120 VAC Resistive
- Environmental Exposure 0° to 350° F (-18° to 177° C)
- UL recognized and CSA certified and European Approved
- Single-Pole, Single-Throw (SPST)
- Pre-set and Tamperproof
- Variety of Mounting Brackets and Terminals Available

SERIES 3450/3450R/3455R/3455RBV 15 AMP THERMOSTATS

Standard Temperature Characteristics

Operating Temperature Range The tightest specification determines the group	Tolerance Allowable ^a ± at mean temperature set points				Standard Mean Differential Nominal degrees between opening and closing points		Price Group ^a
	Open ±°F ±°C		Close ±°F ±°C		°F	°C	
32° to 79°F 0° to 25°C	5	2.8	8	4.4	30-50	16-28	I
	5	2.8	7	3.9	25-29	14-16	II
	5	2.8	6	3.3	20-24	11-13	III
	5	2.8	6	3.3	15-19	8-11	IV
80° to 200°F 25° to 95°C	5	2.8	8	4.4	30-50	16-28	I
	5	2.8	7	3.9	25-29	14-16	II
	5	2.8	6	3.3	20-24	11-14	III
	6	2.2	5	2.8	15-19	8-11	IV
201 to 250°F 96° to 120°C	6	4.4	8	4.4	30-50	16-28	I
	6	3.9	7	3.9	25-29	14-16	II
	6	3.3	6	3.3	20-24	11-14	III
	6	2.8	6	2.8	15-19	8-11	IV
251 to 302°F 121.7° to 148.9°C	7	3.9	8	4.4	30-50	16-28	I
	7	3.9	7	3.9	30-50	16-28	II
	7	3.9	7	3.9	20-29	11-16	III
	6	3.3	7	3.9	15-19	8-11	IV

^aGrouped according to level of accuracy required. Group I with greatest latitude is less expensive than Group II, etc. Please consult factory for temperature ranges, tolerances and differentials not noted. The operating temperature ranges include tolerances.

The ± tolerances shown have been established after careful review of many thermostat applications. Attempts should be made to establish the widest acceptable tolerance possible. For example, the chart may list a tolerance of ±5°F (±2.8°C); however, ±6°F (±3.3°C) may be acceptable for the application at reduced cost.

Note: Temperature checking methods may be slightly different, and allowance for a 1.8°F (1°C) variance should be considered.

See Section B of the Terminal and Bracket Guide for dimensional characteristics.



Operating Parameters

Dielectric Strength	MIL-STD-202 Method 301 -2000 VAC 60 Hz - Terminal to Case
Insulation Resistance	MIL-STD-202 Method 302 Cond. B - 500 Megohms - 500 Volts DC applied
Environmental Exposure	0° to 350°F (-18° to 177°C)
Operating Temp. Range	32° to 302°F (0° to 150°C)
Contact Resistance	MIL-STD-202, Method 307 - 50 Milliohms
Marking	MIL-STD-1285
Weight	6 Grams (Brackets and wire leads not included)
Materials	Base: Phenolic Terminals: Plated Brass or Steel Closure: Aluminum, Stainless Steel, or Brass Brackets: Aluminum, Stainless Steel, or Brass Contacts: Silver

UL and CSA Listings

UL and CSA Listings are for use in equipment where the acceptability of the combination of the thermostat and equipment is determined by Underwriters' Laboratories, Inc. and/or the Canadian Standards Association.

UL File E36103, UL File SA4469 (3455RBV only), UL File MH8267 (3455R only), CSA File 21048.



MAGNET WIRING SCHEMATIC

MACHINE SPECIFICATIONS

PILE FILTER	76 mm (2")
PILE D-SEAL	D-76mm (0.3")
PILE COPS	PLURONOL 76mm (2")
	146295 38mm (1.5")
COLLS Filter per column	
MAX RESISTANCE	0.55 Bar
MAX FLOW	1000 L/min
MAX PRESS (10°C)	50 MPa
MAX INDOOR AIR	60 m/s
COLL INCL	2.5 (v) (0.6 GPH) at 0.25 BAR (1 PSI)
TEMPER. INTERLOCK	OPEN (CLOS) ABOVE 50°C (125°F)
	124 mm (5") (2.5 inch)

NOTE: DO NOT EXCEED THE MAXIMUM SPECIFIED COIL RESISTANCE OR COIL OVERHEATING AND POSSIBLE DAMAGE MAY OCCUR.

REVISIONS			
REV	DESCRIPTION	DATE	APPROVED
A	RELEASE	06/17/93	A. MARTIN
B	NEW 1/8, CORRECT ON 45, ADD ITEM 46 TO 42	06/18/93	EDUCR/AS
C	ADD ITEM 43-44, CHG ITEM 37, ITEM 15 P/N CHANGE	06/27/93	EDUCR/AS

[illegible]





POWER TEN MODEL: P62B-3066A POWER SUPPLY




NOTE

1. POWER SUPPLY SHOWN WITH 2 PHASE 208V AC INPUT
2. REFER TO TABLE ON DWG 139DJ240 FOR AC INPUT RATINGS OTHER THAN 2 PHASE 208V.

M/S=NOT SUPPLIED

7	1	06-81	CABLE TIE ANCHORING MNG. NWL. BAR-10K
6	1	06-81	CABLE TIE ANCHORING 2.5mm NWL. BAR-1K
5	1	14-110S	POWER CABLE TIE SQ 1 CORE 12MM N/S
4	1	115-20P	PLUG SPARE/20D. ANCHOR. BREAKANT
3	1	1313	CABLE CLAMP TROMBS & BETTS
2	1	12B000D10	AC TERMINAL BOX
1	1	11B00D50	CURRENT & INTERLOCK CABLE BIDA
REEL QTY	PART NUMBER		
<div> <div>   </div> <div> <p>DO NOT SCALE</p> <p>ALL DIMENSIONS IN MILLIMETERS & DECIMALS UNLESS OTHERWISE SPECIFIED</p> <p>1st: (850)892-8150, 1st: (850)902-8150</p> <p>GMW</p> <p>INTEGRITY</p> <p>965 Industrial Rd. San Antonio, CA 94070</p> </div> </div>			
<div> <div>   </div> <div> <p>ELECTROLIC ASSEMBLY</p> <p>5403/P/62B - 3066A</p> <p>AI 11900740</p> <p>TOTAL NIS 11900740</p> <p>SHEET 1 OF 1</p> <p>NO</p> <p>A</p> </div> </div>			



TEL	071	number	024366944	fax	
ELECTRICAS		DO NOT SCALE			
SHEET		NO. 001			
TITLE		WIRING DIAGRAM			
DATE		11/10/83			
BY		W. J. B. / J. B. B.			
CHECKED		W. J. B. / J. B. B.			
APPROVED		W. J. B. / J. B. B.			
REVISIONS					
NO.	DATE	DESCRIPTION			
1	11/10/83	WIRING DIAGRAM			
2	11/10/83	WIRING DIAGRAM			
3	11/10/83	WIRING DIAGRAM			
4	11/10/83	WIRING DIAGRAM			
5	11/10/83	WIRING DIAGRAM			
6	11/10/83	WIRING DIAGRAM			
7	11/10/83	WIRING DIAGRAM			
8	11/10/83	WIRING DIAGRAM			
9	11/10/83	WIRING DIAGRAM			
10	11/10/83	WIRING DIAGRAM			
11	11/10/83	WIRING DIAGRAM			
12	11/10/83	WIRING DIAGRAM			
13	11/10/83	WIRING DIAGRAM			
14	11/10/83	WIRING DIAGRAM			
15	11/10/83	WIRING DIAGRAM			
16	11/10/83	WIRING DIAGRAM			
17	11/10/83	WIRING DIAGRAM			
18	11/10/83	WIRING DIAGRAM			
19	11/10/83	WIRING DIAGRAM			
20	11/10/83	WIRING DIAGRAM			
21	11/10/83	WIRING DIAGRAM			
22	11/10/83	WIRING DIAGRAM			
23	11/10/83	WIRING DIAGRAM			
24	11/10/83	WIRING DIAGRAM			
25	11/10/83	WIRING DIAGRAM			
26	11/10/83	WIRING DIAGRAM			
27	11/10/83	WIRING DIAGRAM			
28	11/10/83	WIRING DIAGRAM			
29	11/10/83	WIRING DIAGRAM			
30	11/10/83	WIRING DIAGRAM			
31	11/10/83	WIRING DIAGRAM			
32	11/10/83	WIRING DIAGRAM			
33	11/10/83	WIRING DIAGRAM			
34	11/10/83	WIRING DIAGRAM			
35	11/10/83	WIRING DIAGRAM			
36	11/10/83	WIRING DIAGRAM			
37	11/10/83	WIRING DIAGRAM			
38	11/10/83	WIRING DIAGRAM			
39	11/10/83	WIRING DIAGRAM			
40	11/10/83	WIRING DIAGRAM			
41	11/10/83	WIRING DIAGRAM			
42	11/10/83	WIRING DIAGRAM			
43	11/10/83	WIRING DIAGRAM			
44	11/10/83	WIRING DIAGRAM			
45	11/10/83	WIRING DIAGRAM			
46	11/10/83	WIRING DIAGRAM			
47	11/10/83	WIRING DIAGRAM			
48	11/10/83	WIRING DIAGRAM			
49	11/10/83	WIRING DIAGRAM			
50	11/10/83	WIRING DIAGRAM			
51	11/10/83	WIRING DIAGRAM			
52	11/10/83	WIRING DIAGRAM			
53	11/10/83	WIRING DIAGRAM			
54	11/10/83	WIRING DIAGRAM			
55	11/10/83	WIRING DIAGRAM			
56	11/10/83	WIRING DIAGRAM			
57	11/10/83	WIRING DIAGRAM			
58	11/10/83	WIRING DIAGRAM			
59	11/10/83	WIRING DIAGRAM			
60	11/10/83	WIRING DIAGRAM			
61	11/10/83	WIRING DIAGRAM			
62	11/10/83	WIRING DIAGRAM			
63	11/10/83	WIRING DIAGRAM			
64	11/10/83	WIRING DIAGRAM			
65	11/10/83	WIRING DIAGRAM			
66	11/10/83	WIRING DIAGRAM			
67	11/10/83	WIRING DIAGRAM			
68	11/10/83	WIRING DIAGRAM			
69	11/10/83	WIRING DIAGRAM			
70	11/10/83	WIRING DIAGRAM			
71	11/10/83	WIRING DIAGRAM			
72	11/10/83	WIRING DIAGRAM			
73	11/10/83	WIRING DIAGRAM			
74	11/10/83	WIRING DIAGRAM			
75	11/10/83	WIRING DIAGRAM			
76	11/10/83	WIRING DIAGRAM			
77	11/10/83	WIRING DIAGRAM			




NOTE

1. POWER SUPPLY SHOWN WITH 115V AC INPUT
2. CPU INTERFACE IS OPTIONAL EQUIPMENT
3. REFER TO TABLE ON DWG 13900110 FOR AC INPUT RATINGS OTHER THAN 115V AC INPUT

N/S=NOT SUPPLIED

5	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100
1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100
1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100
1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100
1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100
1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100
1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100
1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100
1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100
1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100
1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100
1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100
1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100
1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100
1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100
1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100
1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100
1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80																				

[illegible]


DO NOT SCALE
FOR WIRING
P.O. BOX 2578, REDWOOD CITY, CA 94064
TEL: (650) 802-0200 FAX: (650) 802-0200
WWW.GMW.COM

REV	DESCRIPTION	SHEET	SAT	DATE
1	REVISION	01	2/01	1/03/2020

R1/60205

2

1



REV	DESCRIPTION	SHEET	SAT	DATE
1	REVISION	01	2/01	1/03/2020

1	1	1	1	1
2	1	1	1	1
3	1	1	1	1
4	1	1	1	1
5	1	1	1	1
6	1	1	1	1
7	1	1	1	1
8	1	1	1	1

DO NOT SCALE
FOR WIRING
P.O. BOX 2578, REDWOOD CITY, CA 94064
TEL: (650) 802-0200 FAX: (650) 802-0200
WWW.GMW.COM


ELECTRICAL WIRING
BOP 2020/2020

REV A

1

PROPRIETARY
THIS DRAWING CONTAINS CONFIDENTIAL INFORMATION
PROCESSED BY GMW INC. IT MUST NOT BE
REPRODUCED OR DISCLOSED TO OTHERS OR USED IN ANY
MANNER THAT VIOLATES THE PATENT RIGHTS OF GMW INC.
OR VIOLATES ANY OTHER APPLICABLE LAWS OR REGULATIONS.
© 1995 GMW INC. ALL RIGHTS RESERVED.

REVISIONS			
REV	DESCRIPTION	DATE	APPROVED
A	RELEASE	06/13/95	G.DOUGLAS




ITEM	QTY	PART NUMBER	DESCRIPTION	NOTE
1	1	11900270	ROLL/ROT BASE ASSY	
2	1	11900270	ROLL/ROT BASE ASSY	
3	1	11900270	ROLL/ROT BASE ASSY	
4	1	11900270	ROLL/ROT BASE ASSY	
5	1	11900270	ROLL/ROT BASE ASSY	
6	1	11900270	ROLL/ROT BASE ASSY	
7	1	11900270	ROLL/ROT BASE ASSY	
8	1	11900270	ROLL/ROT BASE ASSY	
9	1	11900270	ROLL/ROT BASE ASSY	
10	1	11900270	ROLL/ROT BASE ASSY	
11	1	11900270	ROLL/ROT BASE ASSY	
12	1	11900270	ROLL/ROT BASE ASSY	
13	1	11900270	ROLL/ROT BASE ASSY	
14	1	11900270	ROLL/ROT BASE ASSY	
15	1	11900270	ROLL/ROT BASE ASSY	
16	1	11900270	ROLL/ROT BASE ASSY	
17	1	11900270	ROLL/ROT BASE ASSY	
18	1	11900270	ROLL/ROT BASE ASSY	
19	1	11900270	ROLL/ROT BASE ASSY	
20	1	11900270	ROLL/ROT BASE ASSY	
21	1	11900270	ROLL/ROT BASE ASSY	
22	1	11900270	ROLL/ROT BASE ASSY	
23	1	11900270	ROLL/ROT BASE ASSY	
24	1	11900270	ROLL/ROT BASE ASSY	
25	1	11900270	ROLL/ROT BASE ASSY	
26	1	11900270	ROLL/ROT BASE ASSY	
27	1	11900270	ROLL/ROT BASE ASSY	
28	1	11900270	ROLL/ROT BASE ASSY	
29	1	11900270	ROLL/ROT BASE ASSY	
30	1	11900270	ROLL/ROT BASE ASSY	
31	1	11900270	ROLL/ROT BASE ASSY	
32	1	11900270	ROLL/ROT BASE ASSY	
33	1	11900270	ROLL/ROT BASE ASSY	
34	1	11900270	ROLL/ROT BASE ASSY	
35	1	11900270	ROLL/ROT BASE ASSY	
36	1	11900270	ROLL/ROT BASE ASSY	
37	1	11900270	ROLL/ROT BASE ASSY	
38	1	11900270	ROLL/ROT BASE ASSY	
39	1	11900270	ROLL/ROT BASE ASSY	
40	1	11900270	ROLL/ROT BASE ASSY	
41	1	11900270	ROLL/ROT BASE ASSY	
42	1	11900270	ROLL/ROT BASE ASSY	
43	1	11900270	ROLL/ROT BASE ASSY	
44	1	11900270	ROLL/ROT BASE ASSY	
45	1	11900270	ROLL/ROT BASE ASSY	
46	1	11900270	ROLL/ROT BASE ASSY	
47	1	11900270	ROLL/ROT BASE ASSY	
48	1	11900270	ROLL/ROT BASE ASSY	
49	1	11900270	ROLL/ROT BASE ASSY	
50	1	11900270	ROLL/ROT BASE ASSY	
51	1	11900270	ROLL/ROT BASE ASSY	
52	1	11900270	ROLL/ROT BASE ASSY	
53	1	11900270	ROLL/ROT BASE ASSY	
54	1	11900270	ROLL/ROT BASE ASSY	
55	1	11900270	ROLL/ROT BASE ASSY	
56	1	11900270	ROLL/ROT BASE ASSY	
57	1	11900270	ROLL/ROT BASE ASSY	
58	1	11900270	ROLL/ROT BASE ASSY	
59	1	11900270	ROLL/ROT BASE ASSY	
60	1	11900270	ROLL/ROT BASE ASSY	
61	1	11900270	ROLL/ROT BASE ASSY	
62	1	11900270	ROLL/ROT BASE ASSY	
63	1	11900270	ROLL/ROT BASE ASSY	
64	1	11900270	ROLL/ROT BASE ASSY	
65	1	11900270	ROLL/ROT BASE ASSY	
66	1	11900270	ROLL/ROT BASE ASSY	
67	1	11900270	ROLL/ROT BASE ASSY	
68	1	11900270	ROLL/ROT BASE ASSY	
69	1	11900270	ROLL/ROT BASE ASSY	
70	1	11900270	ROLL/ROT BASE ASSY	
71	1	11900270	ROLL/ROT BASE ASSY	
72	1	11900270	ROLL/ROT BASE ASSY	
73	1	11900270	ROLL/ROT BASE ASSY	
74	1	11900270	ROLL/ROT BASE ASSY	
75	1	11900270	ROLL/ROT BASE ASSY	
76	1	11900270	ROLL/ROT BASE ASSY	
77	1	11900270	ROLL/ROT BASE ASSY	
78	1	11900270	ROLL/ROT BASE ASSY	
79	1	11900270	ROLL/ROT BASE ASSY	
80	1	11900270	ROLL/ROT BASE ASSY	
81	1	11900270	ROLL/ROT BASE ASSY	
82	1	11900270	ROLL/ROT BASE ASSY	
83	1	11900270	ROLL/ROT BASE ASSY	
84	1	11900270	ROLL/ROT BASE ASSY	
85	1	11900270	ROLL/ROT BASE ASSY	
86	1	11900270	ROLL/ROT BASE ASSY	
87	1	11900270	ROLL/ROT BASE ASSY	
88	1	11900270	ROLL/ROT BASE ASSY	
89	1	11900270	ROLL/ROT BASE ASSY	
90	1	11900270	ROLL/ROT BASE ASSY	
91	1	11900270	ROLL/ROT BASE ASSY	
92	1	11900270	ROLL/ROT BASE ASSY	
93	1	11900270	ROLL/ROT BASE ASSY	
94	1	11900270	ROLL/ROT BASE ASSY	
95	1	11900270	ROLL/ROT BASE ASSY	
96	1	11900270	ROLL/ROT BASE ASSY	
97	1	11900270	ROLL/ROT BASE ASSY	
98	1	11900270	ROLL/ROT BASE ASSY	
99	1	11900270	ROLL/ROT BASE ASSY	
100	1	11900270	ROLL/ROT BASE ASSY	

05/13/95 4

PROPRIETARY
THIS DRAWING CONTAINS CONFIDENTIAL INFORMATION
AND IS NOT TO BE REPRODUCED OR DISCLOSED TO OTHERS OR USED IN ANY
MANNER WITHOUT THE WRITTEN CONSENT OF GMW INC.
OR WHATEVER OF GMW INC.


REVISIONS			
REV	DESCRIPTION	DATE	APPROVED
A	RELEASE	05/13/95	G.DONIGLAS



ITEM	QTY	PART NUMBER	DESCRIPTION	NOTE
1	1			
2	1			
3	1			
4	1			
5	1			
6	1			
7	1			
8	1			
9	1			
10	1			
11	1			
12	1			
13	1			
14	1			
15	1			
16	1			
17	1			
18	1			
19	1			
20	1			
21	1			
22	1			
23	1			
24	1			
25	1			
26	1			
27	1			
28	1			
29	1			
30	1			
31	1			
32	1			
33	1			
34	1			
35	1			
36	1			
37	1			
38	1			
39	1			
40	1			
41	1			
42	1			
43	1			
44	1			
45	1			
46	1			
47	1			
48	1			
49	1			
50	1			
51	1			
52	1			
53	1			
54	1			
55	1			
56	1			
57	1			
58	1			
59	1			
60	1			
61	1			
62	1			
63	1			
64	1			
65	1			
66	1			
67	1			
68	1			
69	1			
70	1			
71	1			
72	1			
73	1			
74	1			
75	1			
76	1			
77	1			
78	1			
79	1			
80	1			
81	1			
82	1			
83	1			
84	1			
85	1			
86	1			
87	1			
88	1			
89	1			
90	1			
91	1			
92	1			
93	1			
94	1			
95	1			
96	1			
97	1			
98	1			
99	1			
100	1			

PROPRIETARY
THIS DRAWING CONTAINS CONFIDENTIAL INFORMATION
AND IS NOT TO BE REPRODUCED OR DISCLOSED TO OTHERS OR USED IN ANY
MANNER WITHOUT THE WRITTEN CONSENT OF GMW INC.
© 1995 GMW INC.

REVISIONS			
REV	DESCRIPTION	DATE	APPROVED
A	RELEASE	06/13/95	G. DOUGLAS



ITEM	QTY	PART NUMBER	DESCRIPTION	NOTE
PARTS LIST				
DRAWN	G. DOUGLAS	DATE	06/13/95	DO NOT SCALE
CHECK		DATE		FROM DRAWING
ENGINEERING		DATE		REVISIONS & DIMENSIONS
TITLE				
ROTATING BASE ASSY				
MODEL: 5403				
P.O. Box 2578, Redwood City, CA 94064				
Tel: (650)802-8292. Fax: (650)802-8298				
SOFTWARE				
AUTOCAD 13				
SCALE 1:2.5 WT kg				
SHEET 1 OF 1				

4



—


HOLE PATTERN FOR VERTICAL MOUNTING

1000

PARTS LIST

MODEL: 5403

REVISIONS			
REV	DESCRIPTION	DRAWN	APPROVED
A	RELEASE	04/21/94	C. DODD/PLS
B	ADD PHOTO NOTICES	06/1/90	F. TORRES





MOUNTING HOLES
A=0-0.05 DIRECT MOUNTING
B=34.73/34.72 DIRECT MOUNTING
C1/C2=34.72 45° MOUNTING
D1/D2=34.73 45° MOUNTING
C1/C3=34.72 HORIZ MOUNTING
D1/D3=34.73 HORIZ MOUNTING
E=4RD SPECIAL MOUNTING
F=4RD MOTOR DRIVE MOUNTING
NOTE: 2 HOLES=HIDDEN UNIDIR ROTATING BASE

3	4	10N 7261	5AC5, M12 x 16 FLAT HD 5/5		
2	1	11B02290	ROLLING BASE ASSEMBLY		
1	1	11B03170	ROLLING BASE ASSEMBLY		
ITEM QTY	UNIT	NAME	DESCRIPTION	NOTE	
<div style="display: flex; justify-content: space-between;"> <div> <p>ITEM 101</p> <p>QTY 1</p> <p>UNIT 1</p> <p>NAME 101</p> <p>DESCRIPTION 101</p> <p>NOTE 101</p> </div> <div> <p>QTY 101</p> <p>UNIT 101</p> <p>NAME 101</p> <p>DESCRIPTION 101</p> <p>NOTE 101</p> </div> </div>					
<div style="display: flex; justify-content: space-between;"> <div> <p>ITEM 102</p> <p>QTY 1</p> <p>UNIT 1</p> <p>NAME 102</p> <p>DESCRIPTION 102</p> <p>NOTE 102</p> </div> <div> <p>QTY 102</p> <p>UNIT 102</p> <p>NAME 102</p> <p>DESCRIPTION 102</p> <p>NOTE 102</p> </div> </div>					
<div style="display: flex; justify-content: space-between;"> <div> <p>ITEM 103</p> <p>QTY 1</p> <p>UNIT 1</p> <p>NAME 103</p> <p>DESCRIPTION 103</p> <p>NOTE 103</p> </div> <div> <p>QTY 103</p> <p>UNIT 103</p> <p>NAME 103</p> <p>DESCRIPTION 103</p> <p>NOTE 103</p> </div> </div>					
<div style="display: flex; justify-content: space-between;"> <div> <p>ITEM 104</p> <p>QTY 1</p> <p>UNIT 1</p> <p>NAME 104</p> <p>DESCRIPTION 104</p> <p>NOTE 104</p> </div> <div> <p>QTY 104</p> <p>UNIT 104</p> <p>NAME 104</p> <p>DESCRIPTION 104</p> <p>NOTE 104</p> </div> </div>					
<div style="display: flex; justify-content: space-between;"> <div> <p>ITEM 105</p> <p>QTY 1</p> <p>UNIT 1</p> <p>NAME 105</p> <p>DESCRIPTION 105</p> <p>NOTE 105</p> </div> <div> <p>QTY 105</p> <p>UNIT 105</p> <p>NAME 105</p> <p>DESCRIPTION 105</p> <p>NOTE 105</p> </div> </div>					
<div style="display: flex; justify-content: space-between;"> <div> <p>ITEM 106</p> <p>QTY 1</p> <p>UNIT 1</p> <p>NAME 106</p> <p>DESCRIPTION 106</p> <p>NOTE 106</p> </div> <div> <p>QTY 106</p> <p>UNIT 106</p> <p>NAME 106</p> <p>DESCRIPTION 106</p> <p>NOTE 106</p> </div> </div>					
<div style="display: flex; justify-content: space-between;"> <div> <p>ITEM 107</p> <p>QTY 1</p> <p>UNIT 1</p> <p>NAME 107</p> <p>DESCRIPTION 107</p> <p>NOTE 107</p> </div> <div> <p>QTY 107</p> <p>UNIT 107</p> <p>NAME 107</p> <p>DESCRIPTION 107</p> <p>NOTE 107</p> </div> </div>					
<div style="display: flex; justify-content: space-between;"> <div> <p>ITEM 108</p> <p>QTY 1</p> <p>UNIT 1</p> <p>NAME 108</p> <p>DESCRIPTION 108</p> <p>NOTE 108</p> </div> <div> <p>QTY 108</p> <p>UNIT 108</p> <p>NAME 108</p> <p>DESCRIPTION 108</p> <p>NOTE 108</p> </div> </div>					
<div style="display: flex; justify-content: space-between;"> <div> <p>ITEM 109</p> <p>QTY 1</p> <p>UNIT 1</p> <p>NAME 109</p> <p>DESCRIPTION 109</p> <p>NOTE 109</p> </div> <div> <p>QTY 109</p> <p>UNIT 109</p> <p>NAME 109</p> <p>DESCRIPTION 109</p> <p>NOTE 109</p> </div> </div>					
<div style="display: flex; justify-content: space-between;"> <div> <p>ITEM 110</p> <p>QTY 1</p> <p>UNIT 1</p> <p>NAME 110</p> <p>DESCRIPTION 110</p> <p>NOTE 110</p> </div> <div> <p>QTY 110</p> <p>UNIT 110</p> <p>NAME 110</p> <p>DESCRIPTION 110</p> <p>NOTE 110</p> </div> </div>					
<div style="display: flex; justify-content: space-between;"> <div> <p>ITEM 111</p> <p>QTY 1</p> <p>UNIT 1</p> <p>NAME 111</p> <p>DESCRIPTION 111</p> <p>NOTE 111</p> </div> <div> <p>QTY 111</p> <p>UNIT 111</p> <p>NAME 111</p> <p>DESCRIPTION 111</p> <p>NOTE 111</p> </div> </div>					
<div style="display: flex; justify-content: space-between;"> <div> <p>ITEM 112</p> <p>QTY 1</p> <p>UNIT 1</p> <p>NAME 112</p> <p>DESCRIPTION 112</p> <p>NOTE 112</p> </div> <div> <p>QTY 112</p> <p>UNIT 112</p> <p>NAME 112</p> <p>DESCRIPTION 112</p> <p>NOTE 112</p> </div> </div>					
<div style="display: flex; justify-content: space-between;"> <div> <p>ITEM 113</p> <p>QTY 1</p> <p>UNIT 1</p> <p>NAME 113</p> <p>DESCRIPTION 113</p> <p>NOTE 113</p> </div> <div> <p>QTY 113</p> <p>UNIT 113</p> <p>NAME 113</p> <p>DESCRIPTION 113</p> <p>NOTE 113</p> </div> </div>					
<div style="display: flex; justify-content: space-between;"> <div> <p>ITEM 114</p> <p>QTY 1</p> <p>UNIT 1</p> <p>NAME 114</p> <p>DESCRIPTION 114</p> <p>NOTE 114</p> </div> <div> <p>QTY 114</p> <p>UNIT 114</p> <p>NAME 114</p> <p>DESCRIPTION 114</p> <p>NOTE 114</p> </div> </div>					
<div style="display: flex; justify-content: space-between;"> <div> <p>ITEM 115</p> <p>QTY 1</p> <p>UNIT 1</p> <p>NAME 115</p> <p>DESCRIPTION 115</p> <p>NOTE 115</p> </div> <div> <p>QTY 115</p> <p>UNIT 115</p> <p>NAME 115</p> <p>DESCRIPTION 115</p> <p>NOTE 115</p> </div> </div>					
<div style="display: flex; justify-content: space-between;"> <div> <p>ITEM 116</p> <p>QTY 1</p> <p>UNIT 1</p> <p>NAME 116</p> <p>DESCRIPTION 116</p> <p>NOTE 116</p> </div> <div> <p>QTY 116</p> <p>UNIT 116</p> <p>NAME 116</p> <p>DESCRIPTION 116</p> <p>NOTE 116</p> </div> </div>					
<div style="display: flex; justify-content: space-between;"> <div> <p>ITEM 117</p> <p>QTY 1</p> <p>UNIT 1</p> <p>NAME 117</p> <p>DESCRIPTION 117</p> <p>NOTE 117</p> </div> <div> <p>QTY 117</p> <p>UNIT 117</p> <p>NAME 117</p> <p>DESCRIPTION 117</p> <p>NOTE 117</p> </div> </div>					
<div style="display: flex; justify-content: space-between;"> <div> <p>ITEM 118</p> <p>QTY 1</p> <p>UNIT 1</p> <p>NAME 118</p> <p>DESCRIPTION 118</p> <p>NOTE 118</p> </div> <div> <p>QTY 118</p> <p>UNIT 118</p> <p>NAME 118</p> <p>DESCRIPTION 118</p> <p>NOTE 118</p> </div> </div>					
<div style="display: flex; justify-content: space-between;"> <div> <p>ITEM 119</p> <p>QTY 1</p> <p>UNIT 1</p> <p>NAME 119</p> <p>DESCRIPTION 119</p> <p>NOTE 119</p> </div> <div> <p>QTY 119</p> <p>UNIT 119</p> <p>NAME 119</p> <p>DESCRIPTION 119</p> <p>NOTE 119</p> </div> </div>					
<div style="display: flex; justify-content: space-between;"> <div> <p>ITEM 120</p> <p>QTY 1</p> <p>UNIT 1</p> <p>NAME 120</p> <p>DESCRIPTION 120</p> <p>NOTE 120</p> </div> <div> <p>QTY 120</p> <p>UNIT 120</p> <p>NAME 120</p> <p>DESCRIPTION 120</p> <p>NOTE 120</p> </div> </div>					
<div style="display: flex; justify-content: space-between;"> <div> <p>ITEM 121</p> <p>QTY 1</p> <p>UNIT 1</p> <p>NAME 121</p> <p>DESCRIPTION 121</p> <p>NOTE 121</p> </div> <div> <p>QTY 121</p> <p>UNIT 121</p> <p>NAME 121</p> <p>DESCRIPTION 121</p> <p>NOTE 121</p> </div> </div>					
<div style="display: flex; justify-content: space-between;"> <div> <p>ITEM 122</p> <p>QTY 1</p> <p>UNIT 1</p> <p>NAME 122</p> <p>DESCRIPTION 122</p> <p>NOTE 122</p> </div> <div> <p>QTY 122</p> <p>UNIT 122</p> <p>NAME 122</p> <p>DESCRIPTION 122</p> <p>NOTE 122</p> </div> </div>					
<div style="display: flex; justify-content: space-between;"> <div> <p>ITEM 123</p> <p>QTY 1</p> <p>UNIT 1</p> <p>NAME 123</p> <p>DESCRIPTION 123</p> <p>NOTE 123</p> </div> <div> <p>QTY 123</p> <p>UNIT 123</p> <p>NAME 123</p> <p>DESCRIPTION 123</p> <p>NOTE 123</p> </div> </div>					

[illegible]

PROPRIETARY
THIS DRAWING CONTAINS CONFIDENTIAL INFORMATION
PROCESSED BY GMW INC. IT MUST NOT BE
REPRODUCED OR DISCLOSED TO OTHERS OR USED IN ANY
MANNER THAT VIOLATES THE PATENT RIGHTS OF GMW
INC. OR VIOLATES ANY APPLICABLE LAWS.
© 1993 GMW INC.

REVISIONS				
REV	DESCRIPTION	DATE	APPROVED	
A	RELEASE	05/16/93	A. MARTIN	




- NOTES
1. MATERIAL: 127 X 63 X 15 M.S. CHANNEL
 2. DE BURR & BREAK SHARP EDGES
 3. FINISH: PAINT PRECISION TAN TO BSL: T783800010

ITEM	QTY	PART NUMBER	DESCRIPTION	NOTE
1	1			
2	1			
3	1			
4	1			
5	1			
6	1			
7	1			
8	1			
9	1			
10	1			
11	1			
12	1			
13	1			
14	1			
15	1			
16	1			
17	1			
18	1			
19	1			
20	1			
21	1			
22	1			
23	1			
24	1			
25	1			
26	1			
27	1			
28	1			
29	1			
30	1			
31	1			
32	1			
33	1			
34	1			
35	1			
36	1			
37	1			
38	1			
39	1			
40	1			
41	1			
42	1			
43	1			
44	1			
45	1			
46	1			
47	1			
48	1			
49	1			
50	1			
51	1			
52	1			
53	1			
54	1			
55	1			
56	1			
57	1			
58	1			
59	1			
60	1			
61	1			
62	1			
63	1			
64	1			
65	1			
66	1			
67	1			
68	1			
69	1			
70	1			
71	1			
72	1			
73	1			
74	1			
75	1			
76	1			
77	1			
78	1			
79	1			
80	1			
81	1			
82	1			
83	1			
84	1			
85	1			
86	1			
87	1			
88	1			
89	1			
90	1			
91	1			
92	1			
93	1			
94	1			
95	1			
96	1			
97	1			
98	1			
99	1			
100	1			

PROPRIETARY
THIS DRAWING CONTAINS CONFIDENTIAL INFORMATION
AND IS NOT TO BE REPRODUCED OR DISCLOSED TO OTHERS OR USED IN ANY
MANNER WITHOUT THE WRITTEN CONSENT OF GMW INC.
© 1993 GMW INC.

REVISIONS			
REV	DESCRIPTION	DATE	APPROVED
A	RELEASE	05/16/93	A. MARTIN



- NOTES
1. MATERIAL: M/S PLATE 6MM THICK
 2. DE BURR & BREAK SHARP EDGES 0.2MM
 3. FINISH: PAINT PRECISION TAN TO BSL: TP85800010
 4. NO REQD: 2 PER MAGNET.

ITEM	QTY	PART NUMBER	DESCRIPTION	NOTE
PARTS LIST				
DRAWN A. MARTIN	DATE 05/14/93	DO NOT SCALE	FROM: DRAWING REVISIONS & DIMENSIONS MATCH DRAWING SPECIFICATIONS	
CHECK	DATE	DATE	P.O. Box 2578, Redwood City, CA 94064 Tel: (650)802-8292 Fax: (650)802-8298.	
ENGINEERING	DATE	DATE	TITLE ANGLE BRACKET MODEL: 5403	
	DATE	DATE	SHEET 17612650	
	DATE	DATE	REV A	
	DATE	DATE	SCALE 1:2	
	DATE	DATE	SHEET 1 OF 1	
	DATE	DATE	SOFTWARE: AUTOCAD 13	


4

3




N1

—

REVISIONS			
REV	DESCRIPTION	DRAFT	DATE
A	RELEASE		05/17/93
B	CHG POLE DIAMETER		08/24/98
C	CHG DEPTH OF UNDERCUT AREA ON REAR OF POLE		05/11/99



1. MATERIAL: 1008 LDF CARBON STEEL
2. MATERIAL MUST BE CUT WITH THE AXIS OF THE POLE RUNNING IN THE SAME DIRECTION AS THE RAY PLATE GRAIN
3. ROUGH MACHINE THEN ANNEAL TO BSL: TP95800040
4. FINISH: E, N PLATE 0.01 THICK TO BSL, TP95800120

ITEM	QTY	PART NUMBER	DESCRIPTION	NOTE
PARTS LIST				
DRAWING A. MARTIN		DATE 05/11/93	 GMW P.O. Box 2578, Redwood City, CA 94064 Tel: (650)802-8292, Fax: (650)802-8298.	
CHECK	DATE	DO NOT SCALE FROM DRAWING Dimensions & materials values brackets specify		
ENGINEERING	DATE	LINE IN	NOTES/REV	TITLE
		2.0X3	A.000	48.03
		2.0X	A.01	48.1
		2.0	5.03	50.3
		2.1	5.05	51
		DESA	5.0	50.5
		FINISH	5/4	1.00
NEXT ASSY		THIRD ANGLE PROJECTION		
SOFTWARE AUTOCAD 1.3		 		
SCALE 1:1		WT kg	5-ct 1	OF 1
A2		17612620	REV	C
POLE 76MM MODEL: 5403				

4

2


- A

4

A

○

4

2


- | | |
|--|--|
| | |
|--|--|

- [illegible]

1

PROSPECT ADVICE
This offering is being made by prospectus only. The prospectus contains important information about this offering. It is important that you read the prospectus carefully before you decide whether to invest in this offering. The prospectus also contains information about the risks of investing in this offering. The prospectus is available to you at no charge. You may also obtain a copy of the prospectus by calling 1-800-368-3683 or by writing to the issuer.

REVIEWS			
REV	REMARKS	DATE	AMOUNT
A	RELEASE		
B	INTERLAIDS AND SOT PLACING	04/23/94	ELBOUGA

[illegible]